

LMR Master™ S412E Overview



Anritsu
envision : ensure


LMR Master S412E



- Combines two industry-leading products:
 - Spectrum Master™ Spectrum Analyzer
 - Performance + Features
 - Site Master™ Cable and Antenna Analyzer
 - 2 Port, 1 Path Vector Network Analyzer
 - 100 dB transmission dynamic range
- Adds: 1.6 GHz LMR Signal Generator
 - 0 to -130 dB range , 0.1 dB resolution
- Adds: LMR Signal Analyzers
 - P25 Phase 1 & Phase 2
 - TETRA
 - DMR (MotoTRBO™)
 - dPMR
 - NXDN™
 - NBFM
 - LTE (FirstNet) and GSM
 - PTC (Positive Train Control)
 - Transmitter and receiver measurements
 - Indoor and outdoor coverage mapping


Spectrum Analyzer Highlights

- Measurements
 - Occupied Bandwidth, Channel Power, ACPR, C/I, Coverage Mapping
 - EMF Measurement System (Option 444)
 - Interference Analyzer (Option 25)
 - Spectrogram, Signal Strength, RSSI, Mapping
- Frequency Coverage
 - 9 kHz to 1.6 GHz (Optional extension to 6 GHz)
- Dynamic Range
 - > 95 dB in 10 Hz RBW
- DANL
 - -152 dBm in 10 Hz RBW
- Phase Noise
 - -100 dBc/Hz max @ 10 kHz offset at 1 GHz
- Frequency Accuracy
 - 120 ppb standard (25 °C ± 25 °C)
 - < 50 ppb after 3 minutes with GPS lock



Vector Network Analyzer (VNA) Highlights




- 1-path, 2-port VNA with user-friendly Field Mode interface
- Display Options
 - Single, Dual, and 2 Trace Overlay
- Frequency Coverage
 - 500 kHz to 1.6 GHz (Optional extension to 6 GHz)
- Calibration Stability
 - up to 16 hours
- Data Points
 - up to 4001
- IF Bandwidth
 - 10 Hz to 100 kHz
- Dynamic Range
 - 100 dB transmission
- Sweep Speed
 - 850 us/data point



Tetra testing

S412E is able to show

- Constellation Diagram
- TETRA Spectrum Graph
- TETRA Eye Diagram
- Summary Graph
- TETRA Summary Graph



Summary

Rx Freq	3.000 GHz
Rx Pattern	TETRA OTA
Mod Type	Base Station
Rx Pwr Offset	0.0 dB Ext Loss
Auto Rx Range	OFF
Preamp	OFF
Tx Freq	800.000 MHz
Coupling	OFF
Tx Pattern	OT
Tx Output	OFF
Tx Output Lvl	0.0 dBm
Tx Pwr Offset	0.0 dB Ext Loss
Squelch Lvl	-100.0 dBm
Ref Source	Int Std Accy


Received Pwr	-77.85 dBm
Freq Error	-1744.75 Hz
RMS Vec Err	73.54%
Peak Vec Err	247.06%
BER	--
Resid Carr Mag	85.44%
IQ Imbal	-37.49 dB
Phase Error	26.26°
Mag Error	57.36%
Sym Rate Err	-415.01 mHz

TETRA Summary


BS ECC	1060FA79h
Mobile CC	0262
Mobile NC	01001
Base CC	57
LAC	05537
MS Max Tx Pwr	30 dBm

TETRA Base Station Sensitivity Measurements

- Synchronizes to TETRA Base Station
- Generates T1 TCH/7.2 signal
- Internal & External Sync
- Supports all major TETRA Base Station manufacturers




Hytera Base Station Setup




- Connect the MA25200A Input Protection Module/attenuator to the Hytera base station
- Connect the TB3 base station to a PC with the test software

Live DMR Repeater Sensitivity Measurements


- Make DMR Repeater Receiver Sensitivity measurement on a live site
- LMR Master
 - Wakes up DMR Repeater
 - Generates 1031 Hz signal for audible reference
 - Loopback BER measurement on LMR Master




DMR Repeater Sensitivity Measurement Setup Example



Handheld Transceiver connected to LMR Master




- S412E LMR Master to analyze the modulation quality and receiver sensitivity of a handheld transceiver (HT).



Only LMR Solution with Interference Hunting (Future upgrade)



- Spectrogram
 - 48 hours of spectrum history
- Channel Scanner
- Map on screen with antenna / compass for triangulation



Propagation testing


Radio propagation is the way radio signals are transmitted from one point to another point

S412E can transmit Tetra signal and receive the Tetra signal simultaneously.




Only LMR Solution with LTE Measurements (Future upgrade)

- LTE will evolve to being the go-to mission critical standard
 - FirstNet (USA), ESN (UK), SafeNet (South Korea)
 - Major LMR manufacturers releasing LTE solutions
- LMR Master is the only instrument that can measure both LMR and LTE systems
 - Measure LTE transmitter
 - Analyze LTE modulation



GLOBAL INSTALLED BASE OF MISSION CRITICAL VOICE DEVICES SPLIT BY TECHNOLOGY (million units, end of year)




Source: IHS Markit

April - 2018

Only LMR Solution with Remote Control with Built-In Web Server

- Supports all modes and functions of the LMR Master
- Use any web browser
- Supports
 - Cell phones
 - Tablets
 - Laptop computers
 - Desktop computers



Questions?

